

Single-axis
BASIC UNIVERSAL



Control units

## Single-axis ■ BASIC UNIVERSAL



Regardless of your preferred type of control communication, BASIC UNIVERSAL offers you a wide range of industry-standard interfaces. As a result, this control unit is well suited for a variety of applications – including those in your industry. The correct interface for connecting the IndraDyn motors or other standardized encoders, such as Hiperface<sup>®</sup>, is already integrated. In addition, this control unit has an empty slot for the connection of another encoder, connection of the analog I/O extension or for the emission of emulated encoder signals. An additional plug-in MultiMediaCard gives you the option of simple transmission or duplication of your drive parameters. This card can also be used to expand the memory for the motion logic integrated in the drive (firmware option). For an easy start-up use a PC with the Rexroth IndraWorks engineering framework.

## **Technical data**

recinital data			
IndraDrive control units			
Master communication			
Parallel interface			
PROFIBUS			
SERCOS 2			
SERCOS III			
Multi-Ethernet			
CANopen			
DeviceNet			
Configurations			
Option 1	Encoder interface	•	
Option 2	Additional Interface 1	•	
Safety option		•	
Slot for MultiMediaCard		•	
Encoder interfaces			
IndraDyn motors MSK, MKE, MAD and MAF, Hiperface®, 1 Vpp and 5 V TTL		•	
MHD and MKD motors			
EnDat 2.1, 1 Vpp and 5 V TTL			
Safety options compliant with EN 13849-1 und EN 62061			
Safe Torque Off (Cat. 3 PL e/SIL 3)			
Expansions			
Encoder emulation			
Analog in-/outputs (extension)			

## Single-axis ■ BASIC UNIVERSAL

Software module		
MultiMediaCard		
Operation panel		
Standard		•
Cycle times		
Current control	[µs]	125
Velocity control	[µs]	250
Position control	[µs]	500
PWM frequency		
4 kHz		•
Inputs/outputs		
Digital inputs		5
Digital inputs utilizable for touch probes		1
Digital inputs/outputs (user-defined settings)		3
Analog inputs		1
Analog outputs		2
Relay outputs		1
Interfaces		
RS232		•
Control voltage data		
Control Voltage		24 VDC
Power consumption without options	[W]	6.5

- Basic configurationOption

Representante oficial de:



[Argentina]



Calle 49 N $^\circ$  5764 - Villa Ballester (B1653AOX) - Prov. de Buenos Aires - ARGENTINA Tel: (+54 11) 4768-4242 / Fax: (+54 11) 4849-1212

Mail: ventas@nakase.com.ar / Web: www.nakase.com.ar